



ELECTRONICS, INC.
44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089
<http://www.nteinc.com>

NTE1529 Integrated Circuit Dual OP Amp

Description:

The NTE1529 is a dual operational Amplifier with a phase compensation circuit built-in. It is suited for application to various electronic circuits such as active filters and audio preamplifiers.

Features:

- Phase Compensation Circuit
- High Gain, Low Noise
- Output Short-Circuit Protection
- Two Circuits Symmetrically Arranged in 9-Lead plastic SIP Package

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Voltage, Supply Voltage, V_{CC}, V_{EE}	$\pm 18\text{V}$
Differential Input Voltage, V_{ID}	$\pm 30\text{V}$
Common-Mode Input Voltage, V_{ICM}	$\pm 15\text{V}$
Power Dissipation, P_D	500mW
Operating Ambient Temperature Range, T_{opr}	$-20^\circ \text{ to } +75^\circ\text{C}$
Storage Temperature Range, T_{stg}	$-55^\circ \text{ to } +125^\circ\text{C}$

Electrical Characteristics: ($V_{CC} = 15\text{V}, V_{EE} = -15\text{V}, T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Input Offset Voltage	$V_{I(\text{offset})}$	$R_S \leq 10\text{k}\Omega$	–	0.5	6	mV
Input Offset Current	I_{10}		–	5	200	nA
Input Bias Current	I_{BIAS}		–	–	500	nA
Voltage Gain	G_V	$R_L \geq 2\text{k}\Omega, V_O = \pm 10\text{V}$	86	100	–	dB
Maximum Output Voltage	$V_{O(\text{max})}$	$R_L \geq 10\text{k}\Omega$	± 12	± 14	–	V
		$R_L \geq 2\text{k}\Omega$	± 10	± 13	–	V
Common-Mode Input Voltage Width	V_{CM}		± 12	± 14	–	V
Common-Mode Rejection Ratio	CMR		70	90	–	dB
Supply Voltage Rejection Ratio	SVR		–	30	150	$\mu\text{V/V}$
Power Consumption	P_C	$R_L = \infty$	–	90	170	mW
Slew Rate	SR	$R_L \geq 2\text{k}\Omega$	–	1.0	–	$\text{V}/\mu\text{s}$
Input Referred Noise Voltage	V_{ni}	$R_s = 1\text{k}\Omega, B = 10\text{Hz} \sim 30\text{kHz}$	–	2.5	–	μV_{rms}

Pin Connection Diagram
(Front View)

